

Overview

The Marshalling Clock features Hours, Minutes, Seconds and Hundreds of a Second. Its primary function is to hold the time of day for logging purposes when a competitor completes a stage of the competition, then restore the current time of day after the competitors time has been recorded.

Features:

- Displays HH:MM:SS:MSMS spread over two 4 digit LCD Screens
- Back-Light Button
 - Factory Modification available – External Switch for Permanent Light ON or OFF
- Memory of last stored Time
- Powered via 9V Battery

Marshalling Clock Use:

- To initialize the Marshalling clock;
 - When you first switch on the unit, the words '**not Set**' appear on the screen.
 - Hold down the **H** Button and momentarily press the **M** Button, then release the **H** button to set the time (Hours:Minutes) in 24Hr format.
 - The **H** Button will swap between the pairs of digits.
 - The **R** Button will swap screens showing (**Hours : Minutes**) or (**Seconds . Hundredths of a Second**) – The difference can be determined by the colon vs single decimal place. This works in both the setting mode and standard mode.
 - The flashing pair of digits can be incremented by repeated pressing of the **S** Button, or can be zeroed with the **Z** Button.
 - When the time has been set hold down the **H** Button and momentarily press the **R** Button, then release the **H** Button to exit the setting mode. *To prevent the time being inadvertently altered in the field; once the time setting mode has been exited, it cannot be reset unless the whole clock is powered down for a few seconds.*
- The **R** Button toggles between (Hours : Minutes) and (Seconds . Hundredths of a Second) being displayed. The Marshal can use this button at any time without affecting anything else.
- Press the **S** Button when the competitor enters the timed point. This freezes the screen with competitors' time and also puts this into the memory, replacing any previously remembered time. Pressing the **R** button at this point will display the whole of the frozen time alternating between Hr:Mins or Secs.Hunds.
- Pressing the **Z** Button restores the screen to the present time of day.
- Pressing the **M** Button will recall the last remembered time to the screen and again **Z** will restore the current time.

Factory Modifications:

These modifications are available from Brantz either as a Special Pre-Order request as an after-market, Retro-fit.

- External Power ON/OFF Switch – 1 slide switch
- External Light Continuous ON/OFF Switch – 1 slide switch
- External Power & Continuous Light ON/OFF Switch – 1 slide switch
- External Power & External Light ON/OFF Switch – 2 slide switches

For more information on these modifications or any other questions you have regarding Brantz Products – Please phone: 0044 (0) 1625 669366 or email: sales@brantz.co.uk
phone: 0044 (0) 1625 669366 or email: sales@brantz.co.uk